

RING SIZES

To find the length you will need to make a ring add twice the depth of metal to the inside circumference.

Eg. To make a ring in size K from 1mm wire.

$$50 + (2 \times 1) = 52\text{mm}$$

UK size	US size	Inside diameter (mm)	Inside circumference (mm)
A	½	12.04	37.8
B	1	12.45	39.1
C	1½	12.85	40.4
D	2	13.26	41.7
E	2½	13.67	42.9
F	3	14.07	44.2
G	3½	14.48	45.5
H	4	14.88	46.8
I	4½	15.29	48
J	4¾	15.49	48.7
K	5¼	15.9	50
L	5¾	16.31	51.2
M	6¼	16.71	52.5
N	6¾	17.12	53.8
O	7¼	17.53	55.1
P	7¾	17.93	56.3
Q	8¼	18.34	57.6
R	8¾	18.75	58.9
S	9¼	19.15	60.2
T	9¾	19.56	61.4
U	10¼	19.96	62.7
V	10¾	20.37	64
W	11¼	20.78	65.3
X	11¾	21.18	66.6
Y	12¼	21.59	67.8
Z	12½	21.79	68.5

